

TABLE OF CONTENTS

1. OVERVIEW.....	1
2. CARD EDGE CONTROLS.....	2
2.1. DETERMINING CURRENT IP ADDRESS SETTINGS.....	2
2.2. RESTORING FACTORY DEFAULTS.....	2
2.3. CARD EDGE LEDS.....	2
3. CONFIGURATION.....	3
3.1. CONFIGURATION STEPS.....	3
3.2. DEBUG/MONITOR PORT CONNECTION	3
3.3. MAIN MENU	5
3.4. NETWORK CONFIGURATION.....	5
3.5. SERIAL PORT SETUP	5
3.5.1. Parameters	5
3.5.2. Back Plate.....	6
3.5.3. RS-232 Wiring	7
3.5.4. RS-422 Wiring	8
3.6. ASCII PLUS PROTOCOL SETUP	9
3.6.1. Supported Commands.....	9
3.6.2. UMD Mapping.....	9
3.6.3. Tally Mapping	9
3.6.4. User Defined Display Mode	9
3.6.5. Display ID Offset.....	10
3.6.6. AP Address 0xFE Remap To 00.....	10
3.7. UNDER MONITOR DISPLAY SETUP	10
4. TROUBLESHOOTING TIPS.....	11
4.1. CHECKING ANDROMEDA COMMUNICATION	11
4.2. CHECKING UMD COMMUNICATION.....	12
5. PERFORMING A FIRMWARE UPGRADE.....	13
5.1. FTP	13
5.2. SERIAL.....	13

Figures

Figure 1-1: Typical 7700PTX-AP Master Mode Setup1

Figure 2-1: PTX Card Edge2

Figure 3-1: Connect To Window.....4

Figure 3-2: COM1 Properties4

Figure 3-3: 7700PTX Back Plate6

Figure 3-4: RS-232 Pins7

Figure 3-5: RS-422 Pins8

Figure 3-6: UMD Peer Configuration.....10

Figure 4-1: Andromeda Status11

Figure 4-2: UMD Peer Status12

Tables

Table 3-1: 7700PTX-AP Main Menu.....5

Table 3-2: Serial Port Parameters.....5

Table 3-3: RS-232 Wiring7

Table 3-4: RS-422 Wiring8

Table 3-5: Display ID Mapping10

REVISION HISTORY

<u>REVISION</u>	<u>DESCRIPTION</u>	<u>DATE</u>
1.0	First Draft	Sept 05
1.1	Minor Corrections	Feb 07
1.2	Standardized Format	Mar 07
1.3	Added ASCII Plus Protocol Setup	Apr 07
1.4	Updated Card Edge drawing	Nov 07

Information contained in this manual is believed to be accurate and reliable. However, Evertz assumes no responsibility for the use thereof nor for the rights of third parties, which may be effected in any way by the use thereof. Any representations in this document concerning performance of Evertz products are for informational use only and are not warranties of future performance, either express or implied. The only warranty offered by Evertz in relation to this product is the Evertz standard limited warranty, stated in the sales contract or order confirmation form.

Although every attempt has been made to accurately describe the features, installation and operation of this product in this manual, no warranty is granted nor liability assumed in relation to any errors or omissions unless specifically undertaken in the Evertz sales contract or order confirmation. Information contained in this manual is periodically updated and changes will be incorporated into subsequent editions. If you encounter an error, please notify Evertz Customer Service department. Evertz reserves the right, without notice or liability, to make changes in equipment design or specifications.

This page left intentionally blank

1. OVERVIEW

The 7700PTX-AP is a protocol translator that can accept, on any of its 4 serial ports, the ASCII Plus protocol generated by Andromeda equipment. The 7700PTX-AP translates the ASCII Plus protocol to the Image Video protocol then transmits it over TCP to a UMD peer. Figure 1-1 shows how the 7700PTX-AP is typically set up.




Figure 1-1: Typical 7700PTX-AP Master Mode Setup

In this example, the Andromeda device is connected to serial port 1 of the 7700PTX-AP. The 7700PTX-AP communicates with two PPVs distributed over two MVP chassis.

2. CARD EDGE CONTROLS

2.1. DETERMINING CURRENT IP ADDRESS SETTINGS

To read the current IP address during normal operation, press the toggle switch DOWN. The IP address can be read on the four-character alphanumeric display.

2.2. RESTORING FACTORY DEFAULTS

To restore all settings to factory defaults, apply power to the card while holding the toggle switch UP until the green LED is illuminated.

2.3. CARD EDGE LEDS

LED 22 is illuminated when Ethernet activity is detected.

All other card edge LEDs are for factory use only.




Figure 2-1: PTX Card Edge

3. CONFIGURATION

3.1. CONFIGURATION STEPS


The basic steps required to configure the 7700PTX-AP are as follows:

1. Connect a PC running a console application to the PTX debug/monitor port via the adapter cable.
2. Configure the network parameters of the 7700PTX-AP.
3. Configure the parameters of each serial port to match those of the connected Andromeda equipment.
4. Enable user-defined display mode if required.
5. Configure the IP address and TCP port of the UMD peer(s).
6. Save all configuration parameters.
7. Power off the 7700PTX-AP.
8. Physically wire the serial port(s) of the 7700PTX-AP to the Andromeda equipment.
9. Power on the 7700PTX-AP.

3.2. DEBUG/MONITOR PORT CONNECTION

The 7700PTX-AP is configured via the debug/monitor port, the header of which is labelled J1. A special Evertz adapter cable allows this port to connect to the COM port of a personal computer. The following steps describe this procedure.

1. Locate the small, keyed, four-pin end of the upgrade cable provided by Evertz.
2. Connect it to the four-pin interface (J1) near the front of the 7700PTX, directly above the card unlock latch.



3. Connect the other end of the upgrade cable to a straight-through serial cable. Connect the serial cable to the serial or COM port of the computer.
4. Initiate HyperTerminal on your computer by selecting:
"Start\Programs\Accessories\Communications\HyperTerminal".
5. Enter a name for your connection, for example: PTX.
6. Press the <Enter> key. A new "Connect To" window opens.



Figure 3-1: Connect To Window

7. Select COM1 for the “*Connect using*” setting. If COM1 is in use, choose an alternate COM port.
8. Press the <Enter> key or select OK. This opens the “*COM Properties*” window.




Figure 3-2: COM1 Properties

9. Enter the information as listed in the screen above.
10. Press the <Enter> key or select OK. The “*COM Properties*” window closes, leaving the HyperTerminal window open.
11. Apply power if the 7700PTX-AP does not have power. The boot sequence and *Main Menu* are displayed in the HyperTerminal window.
12. If the 7700PTX-AP has power, press the <Enter> key to view the 7700PTX-AP’s menu system.
13. Various 7700PTX-AP parameters are configurable via the 7700PTX-AP’s menu system, the root of which is called *Main Menu*.

3.3. MAIN MENU

Table 3-1 lists the entries available in the 7700PTX-AP's *Main Menu*.

Entry	Item	Notes
1	Network Configuration	IP address, subnet mask, gateway, etc.
2	Serial Port Setup	Baud rate, number of data bits, etc. of serial ports that are connected to Andromeda equipment.
3	ASCII Plus Protocol Setup	Permits user-defined display mode.
4	Under Monitor Display Setup	IP address and TCP port of UMD peers.
5	Engineering/Debug	Used for troubleshooting.

Table 3-1: 7700PTX-AP Main Menu

3.4. NETWORK CONFIGURATION

1. From the *Main Menu* select *Network Configuration*.
2. If DHCP (Dynamic Host Configuration Protocol) is desired, then the *Use DHCP* field is set to *True*. Otherwise, the IP address, subnet mask, and gateway (if any) are set and the *Use DHCP* field is set to *False*.
3. Once the network settings are configured, select *Save* and *Exit* before exiting the *Network Configuration* to save the settings, otherwise select *Exit*.



The 7700PTX-AP must be rebooted for any network setting changes to take effect.

3.5. SERIAL PORT SETUP

3.5.1. Parameters

The 7700PTX-AP has 4 serial ports. The parameters associated with each serial port are listed in Table 3-2.

Parameter	Special Notes
Baud Rate	
Data Bits	
Parity	
Stop Bits	
Standard	For serial port 4, only RS-232 is valid.

Table 3-2: Serial Port Parameters



The serial port settings of the 7700PTX-AP must match those of the Andromeda equipment. The 7700PTX-AP must be rebooted for any serial parameter changes to take effect.

3.5.2. Back Plate




Figure 3-3: 7700PTX Back Plate

3.5.3. RS-232 Wiring

Figure 3-4 shows which pins of the back plate are used for RS-232 serial connections.




Figure 3-4: RS-232 Pins

Table 3-3 outlines how to connect the 7700PTX-AP to the Andromeda equipment for RS-232 operation.

7700PTX-AP			Andromeda Equipment
Port	Pin Name	Pin	Pin Name
1	TXA	1	RX
	RXA	2	TX
	GND	6	GND
2	TXB	7	RX
	RXB	8	TX
	GND	12	GND
3	TXC	13	RX
	RXC	14	TX
	GND	22	GND
4	TXD	23	RX
	RXD	24	TX
	GND	26	GND

Table 3-3: RS-232 Wiring

3.5.4. RS-422 Wiring

Figure 3-5 displays which pins of the back plate are used for RS-422 serial connections.




Figure 3-5: RS-422 Pins

Table 3-4 outlines how to connect the 7700PTX-AP to the Andromeda equipment for RS-422 operation.

7700PTX-AP			Andromeda Equipment
Port	Pin Name	Pin	Pin Name
1	TX-A	1	RX-
	TX+A	3	RX+
	RX-A	2	TX-
	RX+A	4	TX+
	GND	6	GND
2	TX-B	7	RX-
	TX+B	9	RX+
	RX-B	8	TX-
	RX+B	10	TX+
	GND	12	GND
3	TX-C	13	RX-
	TX+C	15	RX+
	RX-C	14	TX-
	RX+C	16	TX+
	GND	22	GND

Table 3-4: RS-422 Wiring



The 7700PTX-AP's fourth serial port is not RS-422 capable.

3.6. ASCII PLUS PROTOCOL SETUP

3.6.1. Supported Commands

The 7700PTX-AP supports the following ASCII Plus protocol commands:

1. ZC – Set Color
2. ZD – Display Set
3. ZL – Set Display and Tally Colors (nn = 00, 80, 81)
4. ZM – Set UMD Mode (short format, m ignored)
5. ZT – Set Tally LED (should be done with ZL, ZT fully supported only when user-defined display mode is enabled)

3.6.2. UMD Mapping

On the MVP, UMDs must be associated with a protocol ID. The protocol ID must match that sent by the 7700PTX-AP to the PPV(s).

3.6.3. Tally Mapping

The left ASCII Plus tally corresponds to tally 1 of the MVP. The right ASCII Plus tally corresponds to tally 2 of the MVP. On the MVP, tallies must be associated with a protocol ID. The protocol ID must match that sent by the 7700PTX-AP to the PPV(s).

3.6.4. User Defined Display Mode

Suppose the equipment generating the ASCII Plus protocol does not support the *ZM – Set UMD Mode (short format)* command. For this scenario, a user-defined display mode must be enabled on a per-port basis on the 7700PTX-AP. The user-defined display mode specifies:

- The mode under which the UMD will operate.
- An offset to the ASCII Plus address field.

To activate the user-defined display mode:

1. From the *Main Menu* select *ASCII Plus Protocol Setup*.
2. Select *Display Mode Setup For Serial Port 1* (or select the serial port to which the Andromeda equipment is connected).
3. Select *Enable user-defined display mode* and enter *y* at the prompt.
4. Modify the display ID offset if needed.
5. Select *Save and Exit*.

3.6.5. Display ID Offset

This is the value added to the ASCII Plus address field to obtain the display ID transmitted to the PPV(s). Table 3-5 shows an example using the first 5 ASCII Plus addresses. The ASCII Plus address field is the UMD address received by the 7700PTX-AP. The display ID is the value transmitted by the 7700PTX-AP to the PPV(s).

ASCII Plus Address Field	Serial Port 1 Display ID (Offset = 0)	Serial Port 2 Display ID (Offset = 32)	Serial Port 3 Display ID (Offset = 64)	Serial Port 4 Display ID (Offset = 96)
0	0	32	64	96
1	1	33	65	97
2	2	34	66	98
3	3	35	67	99
4	4	36	68	100

Table 3-5: Display ID Mapping

3.6.6. AP Address 0xFE Remap To 00

Some AP-based equipment uses address 0xFE in place of 0x00. For this case, address 0xFE can be remapped to 0x00 by the 7700PTX-AP provided this setting is enabled.



The 7700PTX-AP does not need to be rebooted for any user-defined display mode changes to take effect.

3.7. UNDER MONITOR DISPLAY SETUP

The 7700PTX-AP has the ability to transmit router source label information to the UMDs of up to 12 PPVs or UMD peers.

Suppose we have the setup of Figure 3-6




Figure 3-6: UMD Peer Configuration

Where:

- An Andromeda device is connected to Serial Port 1 of the 7700PTX-AP.
- The 7700PTX-AP communicates with a PPV with IP address 192.168.18.50, configured to listen for Image Video UMD data on TCP port 9800
- Via the debug console *Main Menu/Under Monitor Display Peer Setup/UMD Peer Setup via Ethernet 1*, configure peer 1 IP address as 192.168.18.50, and its TCP port as 9800.
-




The 7700PTX-AP must be rebooted for any UMD peer changes to take effect.

4. TROUBLESHOOTING TIPS

4.1. CHECKING ANDROMEDA COMMUNICATION

1. From the *Main Menu* select *Engineering/Debug*.
2. Select *Show task statistics*.
3. There are four entries, one for each serial port, listed under the heading *router protocol PCB stats...*. If the item *prot pk rx* is reported as a non-zero hexadecimal value then the 7700PTX-AP is receiving data from the Andromeda equipment. If it is consistently reported as 0x00000000 then the 7700PTX-AP is not receiving data from the Andromeda equipment. In this case the serial settings or wiring may be incorrect or the Andromeda equipment may not be configured properly.



```

dbg_1_115 - HyperTerminal
File Edit View Call Transfer Help

router protocol PCB stats...
1
    prot pkt rx: 0x00000000
    disp set rx: 0x00000000
    set disp tal clr rx: 0x00000000
    set mode rx: 0x00000000
    unk mode rx: 0x00000000
    unsupp rx: 0x00000000
    prot pkt tx: 0x00000000
    ack tx: 0x00000000
    nak tx: 0x00000000
    no mbufs: 0x00000000

2
    prot pkt rx: 0x00000000
    disp set rx: 0x00000000
    set disp tal clr rx: 0x00000000
    set mode rx: 0x00000000
    unk mode rx: 0x00000000
    unsupp rx: 0x00000000
    prot pkt tx: 0x00000000
    ack tx: 0x00000000
    nak tx: 0x00000000
    no mbufs: 0x00000000

Connected 0:04:15  ANSI  115200 8-N-2  SCROLL  CAPS  NUM  Capture  Print echo
  
```

Figure 4-1: Andromeda Status

4.2. CHECKING UMD COMMUNICATION

1. From the *Main Menu* select *Engineering/Debug*.
2. Select *Show task state*.
3. There are up to 12 UMD peer entries listed under the heading *UMD peer status...*. A status reported as *ready* indicates the 7700PTX-AP is able to communicate with that UMD peer. A status consistently reported as something other than *ready* indicates the inability of the 7700PTX-AP to communicate with that UMD peer. Be sure that the UMD peer has been rebooted after being configured to receive the Image Video over TCP.
4. Figure 4-2 shows that the 7700PTX-AP is able to communicate with the UMD peer whose IP address is 192.168.18.40 and who is listening on TCP port 9800.

```

dbg_1_115 - HyperTerminal
File Edit View Call Transfer Help

UMD peer status...
Port      Dst Address      Tcp Port      Status
****      *****
E1        192.168.18.40    9800          ready
E1        0.0.0.0          0             no address set
E1        0.0.0.0          0             no address set
E1        0.0.0.0          0             no address set
E1        0.0.0.0          0             no address set
E1        0.0.0.0          0             no address set
E1        0.0.0.0          0             no address set
E1        0.0.0.0          0             no address set
E1        0.0.0.0          0             no address set
E1        0.0.0.0          0             no address set
E1        0.0.0.0          0             no address set
E1        0.0.0.0          0             no address set

router protocol task state: ready

router protocol PCB state...
1        down
2        ready
3        down
4        down

Connected 2:36:23  ANSI  115200 8-N-2  SCROLL  CAPS  NUM  Capture  Print echo
  
```

Figure 4-2: UMD Peer Status

5. PERFORMING A FIRMWARE UPGRADE

There are two ways to upgrade PTX firmware:

1. Using FTP to perform the upgrade via TCP/IP (*recommended procedure*).
2. Using a terminal application such as *HyperTerminal* to perform the upgrade via a serial connection.

5.1. FTP

1. Open a command prompt window (in Windows: Start/Programs/Accessories/Command Prompt)
2. Enter the location of the firmware file. For example, type `cd c:\temp`.
3. Enter the command `ftp` followed by the PTX IP address.
For example, type `ftp -A 192.168.18.22`.
4. Enter the FTP command `put` followed by the firmware file name. For example, `put ptx.bin`.
5. When the transfer is complete enter the FTP command: `bye`.
6. Step 5 begins the process of saving the firmware to the non-volatile flash of the PTX. The save process is displayed as a percentage on the PTX LCD. Once the process is complete, the PTX LCD again displays the product name and firmware version.
7. Power off the PTX.
8. Power on the PTX.

5.2. SERIAL

1. Power off the PTX.
2. Connect an adapter cable to a PC running a console or terminal application, such as Windows *HyperTerminal*, to the PTX debug/monitor port.
3. Configure the port settings of the terminal program as follows:

Baud	115200
Parity	no
Data bits	8
Stop bits	2
Flow Control	None

4. Set the PTX run/upgrade jumper to the upgrade position.
5. Power on the PTX.
6. After a few moments, the prompt `PPCBOOT>` will appear. Enter the command `upload`.
7. Start the firmware upload on the terminal application (for instance, in *HyperTerminal* select Transfer/Send File...), use Xmodem as the transfer protocol, and select the firmware file. For example, `ptx.bin`.
8. Once the upload is complete the message `upload okay` is displayed.
9. Power off the PTX.
10. Set the PTX run/upgrade jumper to the run position.
11. Remove the serial adapter cable.
12. Power on the PTX.