



Installation Manual

Version 1.08 - February 2009



[XT] Access



XT[2] Gigabit Ethernet Gateway



COPYRIGHT

EVS Broadcast Equipment – Copyright © 2008 - 2009. All rights reserved.

DISCLAIMER

The information in this manual is furnished for informational use only and subject to change without notice. While every effort has been made to ensure that the information contained in this user manual is accurate, up-to-date and reliable, EVS Broadcast Equipment cannot be held responsible for inaccuracies or errors that may appear in this publication.

IMPROVEMENT REQUESTS

Your comments will help us improve the quality of the user documentation. Do not hesitate to send improvement requests, or report any error or inaccuracy in this user manual, by e-mail to doc@evs.tv.

Table of Contents

- TABLE OF CONTENTS 2
- 1. HARDWARE RECOMMENDATIONS 3
- 2. SOFTWARE INSTALLATION 4
- 3. XSECURE MANAGEMENT 11
 - 3.1 LIST OF THE CODES 11
- REGIONAL CONTACTS 12

1. Hardware Recommendations

The XT Access software is installed on a workstation operating under Windows XP or Windows 2003 Server.

The minimum system requirements are:

- Workstation or Laptop
- XP Pro OS, Windows 2003 Server
- CPU Pentium P4, 2.0 Ghz +
- 512 MB RAM
- GigE board with Jumbo Frame capabilities
- VGA 1024x768

The XT Access software runs either on EVS workstations like IPDirector, XFile or XStore , or on any standalone third-party workstation.



Important

Jobs like backup of clips or trains, restore/copy of files to XT use CPU resources on the device where XTAccess runs. It is then advised not to run any other critical application simultaneously on the XTAccess device, especially when the CleanEdit Suite or IPDirector are installed as standalone systems with a local database.

2. Software Installation

The installation package is based on one installshield:

XTAccess_1.08.30_Setup.exe

For the CleanEdit Integration Option, contact the CleanEdit support to install the compliant software.


Installshields are available for CleanEdit v2.06.01 and CleanEdit v2.07.xx.

- o CEXTAccessIntegration_v02.06.36.exe
- o EvsEditFramework_3.06.15.exe


- o CEXTAccessIntegration_v02.07.06.exe
- o EvsEditFramework_3.07.04.exe

To install XTAccess; proceed as follows:


1. Copy the installshield XTAccess_1.08.30_Setup.exe in a temp directory (e.g. C:\Install Software\XTAccess\).
2. Run XTAccess installshield XTAccess_1.08.30_Setup.exe and then follow the steps of the Setup wizard.



3. Press NEXT.



4. Select the destination directory to install the new software and then press **NEXT**.




5. If you install XTAccess for the first time on this workstation, you need to install Microsoft Visual C++ 2005 Redistributable application by selecting "Install VCRedist". For future installations or upgrade, you may deselect this option to reduce installation time.

You can also to select "Install XSecure Manager" and "Install XT-Access Encoders" to install the EVS License software (necessary for the transcoding on the fly which need XSecure code) and all the encoder dll.


Then press **NEXT**.




- 6. Specify the start folder directory and then press **NEXT**.




- 7. Press **INSTALL** to begin the installation of XTAccess.
- 8. If you have selected "Install XSecure Manager": the Xsecure Setup will appear after the installation of XTAccess. Press **NEXT**.




9. Press NEXT.



10. Select the destination directory to install XSecure and then press NEXT.



11. Select the Start Menu Folder for XSecure Manager. Press NEXT.



12. Press INSTALL to begin the installation.



The XSecure software installation is successfully completed. Press **Finish**.




The XTAccess software installation is successfully completed.

Note that a Shortcut of XTAccess has been automatically created on the desktop.

XTAccess icon is the following:



When you first launch XTAccess, the application modifies or adds the TcpAckFrequency in the registry. This key allows having better performances for backup. You need to restart your computer afterwards.



3. XSecure Management

From XAccess v.1.07.22, XSecure is used. XSecure can be installed with XAccess installshield (see software installation chapter).

XSecure uses hardware information from the device where XAccess is running. This means that it is impossible to exchange licenses or codes between devices.

Please refer to the XSecure User's Manual to:

- Start XSecure Manager
- Collect information about your device
- Request a license key from the EVS support
- Import new licenses keys

3.1 LIST OF THE CODES

60 – XAccess

- 10 – Base Package : Not use for the moment
- 20 – Transcoding: Needed to use the transcoding on the fly

Regional Contacts

AMERICA (NORTH & LATIN)

EVS Americas	Tel: +1 973 575 7811 Fax: +1 973 575 7812 Tech. line: +1 973 575 7813	usa@evs.tv
--------------	---	------------

EVS Canada	Tel: +1 514 750 7544 Fax: +1 514 750 7518 Tech. line: +1 973 575 7813	usa@evs.tv
------------	---	------------

ASIA & PACIFIC

EVS Australia	Tel: +61 02 9452 8600 Fax: +61 02 9975 1368 Mobile: +61 420 307 387	sales@evs-asia.com.hk
---------------	---	-----------------------

EVS China	Tel: +86 10 6808 0248 Fax: +86 10 6808 0246 Tech. line: +86 139 1028 9860	evschina@evs.tv
-----------	---	-----------------

EVS Hong-Kong	Tel: +852 2914 2501 Fax: +852 2914 2505 Tech. line: +852 9401 2395	sales@evs-asia.com.hk
---------------	--	-----------------------

EVS India	Tel: +91 22 6697 2999 Fax: +91 22 2673 2092 Mobile: +91 98 9017 5958	sales@evs-asia.com.hk
-----------	--	-----------------------

EUROPE, MIDDLE EAST & AFRICA

EVS Belgium Headquarters	Tel: +32 4 361 7000 Fax: +32 4 391 7099 Tech. line: +32 495 284 000	support@evs.tv sales@evs.tv marketing@evs.tv
-----------------------------	---	--

EVS Brussels	Tel : +32 2 421.78.78 Fax : +32 2 421.78.79	m.dewolf@evs.tv
--------------	--	-----------------

EVS France	Tel: +33 1 46 99 9000 Fax: +33 1 46 99 9009 Tech. line: +33 1 46 99 9003	france@evs.tv
------------	--	---------------

EVS Iberica	Tel: +34 91 490 3930 Fax: +34 91 490 3939 Tech. line: +34 91 490 3933	iberica@evs.tv
-------------	---	----------------


EVS Italy	Tel: +39 030 296 400 Fax: +39 030 294 3650 Tech. line: +39 334 631 1493	italy@evs.tv
-----------	---	--------------

EVS Middle East	Tel: +971 4 365 4222 Fax: +971 4 425 3501 Mobile: +971 50 887 8758	middle-east@evs.tv
-----------------	--	--------------------

EVS UK	Tel: +44 1372 387 250 Fax: +44 1372 387 269 Tech. line: +44 1372 387 266	uk@evs.tv
--------	--	-----------

EVS Broadcast Equipment

Liège Science Park
16, rue Bois St Jean
B-4102 Ougrée
Belgium



Corporate
Headquarters
+32 4 361 7000

North & Latin America
Headquarters
+1 973 575 7811

Asia & Pacific
Headquarters
+852 2914 2501

Other regional offices
available on
www.evs.tv/contact



To learn more about EVS go to www.evs.tv