

Partner Phone Programming

- "Feature-0-0"

-"Intercom, Intercom" (the left intercom button)

This puts you in "System Programming", once there, use the following:

**note – to exit, simply pick up and hang up the handset*

- # 101 System Date Set system date
- # 102 System Day Set system day
- # 103 System Time Set system time
- # 104 Number of Lines Set numbers of trunk lines
- # 105 Transfer Return Rings Transferred call return to originator
- # 107 Recall Timer Durations Time is ms before recall starts
- # 108 Rotary Dialing Timeout Set only for T/R device on a rotary line
- # 109 Outside Conference Denial Allow = 2 outside caller / 3 inside caller
Disallow = 1 outside caller / 4 inside caller
- # 110 ASA Delay - automatic system answer #'s of rings at extension 10 before ASA
- # 111 ASA Button - on LED button only Program a button to turn ASA on / off
- # 112 DXD Delay - direct extension dial #'s of rings at extension 10 before DXD
- # 113 DXD Button - on LED button only Program a button to turn DXD on / off
- # 114 Outside Call Restriction Button - LED Set call restrictions on extension 10
Must program extensions on buttons in order to work
- # 115 Wake Up Service Button - LED Set wake up call service on extension 10
Must program extensions on buttons in order to work
- # 116 / # 320 Call Coverage Rings #'s of rings before coverage extension takes over
- # 117 / # 321 VMS Cover Rings #'s of rings before voice mail takes over
- # 119 Ring On Transfer User hear rings if turned active, must turn off if music

on hold is in use

- # 121 ASA Mode HOLD, DISCONNECT, RING
- # 122 Caller ID Type USA or Singapore
- # 123 Backup Programming Automatically Every 1st day of the month at 2:00 am
- # 124 Backup Programming Manually Manual backup process
- # 125 Restore Programming Restore either auto or manual backup program
- # 126 Automatic Daylight / Standard Times Set auto daylight time adjustment on system
- # 198 Pool Mode - 8632852 Pool mode
- # 198 Key Mode - 8632851 Key mode

- # 201 Dial Mode Set line dial mode to touch tone or rotary
- # 203 Hold Disconnect Time Time to disconnect if put on hold caller disconnects
- # 204 ASA Lines Assign lines to ASA
- # 205 DXD Lines Assign lines to DXD
- # 206 Group Call Distribution - AA Assign lines or hunt group to groups
- # 207 Pool Line Assignment Add lines to pool according to it's pool number
- # 208 Line Coverage Extension Set a backup coverage extension
- # 209 Unique Line Ringing Assign different ring tone to lines

- # 301 Line Assignment Assign lines to extensions
- # 302 Line Access Restriction Set line access restrictions to extensions
- # 303 Display Language Set display languages to extensions
- # 304 Automatic Extension Privacy Prevent other user to intercept a call
- # 305 Abbreviated Ringing Set numbers of ring on a second incoming line while on a phone call
- # 306 Transfer Return Extension Set extension where calls should return
- # 307 Forced Account Code Entry Set to force account code entry before making a call
- # 308 Distinctive Ring Set to have calls to ring differently depends on the source
- # 309 Intercom Dial Tone Set intercom dial tone sounds like a CO dial tone

- # 310 Automatic VMS Cover Route unanswered calls to VM
- # 311 External Hotline Set a specific extension to be a hotline extension. Must be a single line phone, program outgoing phone number into speed dial list (Feature 80)
- # 312 Voice Interrupt on Busy Interrupt a call, program this feature and assign interrupt on busy talk back button. Usage: INTERCOM *ext#
- # 313 Line Access Mode Change extensions from Pool to Key or Key to Pool. All previously programmed lines will be removed
- # 314 Pool Extension Assignment Assign pools to extensions
- # 315 Pool Access Restriction Set dialing permission to pool extensions
- # 316 Call Waiting To activate call waiting feature from the Partner system
- # 317 Caller ID Log Answered Calls Log only answered calls at each extension
- # 318 Caller ID Log Line Association Associate 1 extension to log all calls
- # 319 Caller ID Log All Calls Log all calls at each extension
- # 399 Copy Settings Copy a certain limit of features to another set of phones
- # 401 Outgoing Call Restriction Set call restrictions on lines assigned to extensions
- # 402 Toll Call Prefix Set if 0 or 1 is not require for long distance
- # 403 System Password Root password to override dialing restrictions and turn on/off night service button
- # 404 Disallowed Phone Number Lists Set a list of restricted outgoing phone numbers
- # 405 Disallowed List Assignments Assign disallow list to extensions
- # 406 Emergency Phone Number Lists Numbers regardless of dialing restrictions unless forced account code is in effect
- # 407 Allowed Phone Number Lists Set a list of allowed phone numbers regardless of dialing restrictions
- # 408 Allowed List Assignments Assign allow list to extensions
- # 409 Forced Account Code List Set a list of account codes of up to 99 account codes
- # 410 Star Code Dial Delay Set a certain time delay after the star code

entry

- # 501 Pickup Group Extension Allow others in the pickup group to pick up a call, assign a pickup button
or pickup manually = 66# - group number
- # 502 Calling Group Extension Assign extensions to different groups, allow group paging or ringing
- # 503 Night Service Button Set a button to turn night service on/off
- # 504 Night Service Group Extensions Assign extensions to night service group when the service is turn on
- # 505 Hunt Group Extension Assign extensions to different hunt groups, use group call distribution
to assign lines to groups
- # 506 VMS Hunt Delay Determine how VMS takes over a call after a certain numbers of rings
- # 507 VMS Hunt Schedule Set how VMS handle calls during the day

- # 601 Fax Machine Extension Assign fax extensions, set a fax management button for easy transfer
- # 602 Music On Hold Turn music on hold on or off
- # 603 Hotline Set an internal hotline using the intercom feature only
- # 604 Doorphone 1 Extension Set doorphone extension 1
- # 605 Doorphone 2 Extension Set doorphone extension 2
- # 606 Doorphone Alert Extension Set doorphone alert extension
- # 607 Automated Attendant Extension Set AA extension to allow transfer return, do not use in conjunction with
the VMS' AA
- # 608 SMDR Record Type Set how SMDR should record calls
- # 609 SMDR Top of Page Notify the system after a printer reset or paper problem
- # 610 SMDR Output Format Set the output format, either 15 or 24 digits
- # 611 SMDR Talk Time Records also the length of the call
- # 612 Contact Closure Group Assign extensions to operate contact closure devices
- # 613 Contact Closure Operation Type Set how contact closure operator operates the devices
- # 614 Music On Hold Volume Set volume for music on hold
- # 728 System Reset - SAVED System reset, programming saved
- # 730 Remote Administration Password Set remote password
- # 989 System Reset - NOT SAVED Master reset - password = CLEAR

Button or Dial Code Programming

- F 01 Do Not Disturb - LED
- F 02 Exclusive Hold
- F 03 Recall
- F 04 Save Number Redial
- F 05 Last Number Redial
- F 06 Conference Drop
- F 07 Privacy - LED
- F 08 Touch Tone Enable
- F 09 Message Light On
- F 10 Message Light Off
- F 11 Call Forwarding - LED
- F 12 Account Code Entry - LED
- F 14 VMS Transfer
- F 15 VMS Cover - LED
- F 16 Caller ID Name Display - LED
- F 17 Caller ID Inspect - LED
- F 18 Voice Interrupt on Busy Talk Back - LED
- F 19 Background Music - LED
- F 20 Call Coverage - LED
- F 21 Station Lock - LED
- F 22 Station Unlock
- F 23 Caller ID Logging and Dialing
- F 25 Call Screening
- F 41 Contact Closure 1 - LED
- F 42 Contact Closure 2 - LED
- F 59 System Release Status