

KP9X PHONE OPERATION

KP9X Hang-up Sequence

- 1 Turn off the TIF talk key.
- 2 On the keypad, tap **PHONE-CLR**.
- 3 Turn the TIF talk key on, then off. The TIF key talk and listen indicators will turn off and the TIF-951 "OFF" LED will activate.

KP9X Dial Sequence

- 1 Activate the TIF listen key (listen LED green).
- 2 Make sure the TIF talk key is off (Talk LED off).
- 3 On the keypad, tap **CLR-PHONE-PGM**.
- 4 Activate the TIF talk key (talk LED turns green). The "ON" LED at the TIF-951 will activate, and you should hear dial tone at the KP-32.
- 5 Dial the telephone number. Digits scroll in the display above the TIF talk key.
- 6 When the far end answers, you can dial additional digits (to access a mail system or automated response system, etc.). When finished dialing, momentarily turn off the TIF talk key to end dialing mode (talk LED turns red).
- 7 Turn the TIF talk key back on for conversation.

KP9X Redial Sequence

- 1 Tap the **PHONE** key to activate dialing mode.
- 2 Tap "up" on the TIF key to activate listen.
- 3 Tap **CLR 0 0**. The last phone number will redial.
- 4 After the number has dialed, click the **PHONE** key to end dialing mode.
- 5 If the far end answers, tap "down" on the TIF key to activate talk.
- 6 Use the KP9X hang-up sequence to hang up.

KP9X Autodial Sequences

Storing an Autodial Number in the TIF-951

- 1 Tap the **PHONE** key.
- 2 Tap the TIF talk key to latch it on.
- 3 Using the number keys on the keypad, dial the phone number that you want to store. The entire phone number sequence can have up to 30 digits.
Note To insert one or more pauses anywhere in the dialing sequence, enter **CLR CLR 9 9** for each pause.
- 4 After dialing the telephone number, click **CLR PGM**, then enter a two-digit number (01, 02, etc. up to 32) that you will use as the autodial number.
- 5 After storing the autodial number, hang up using the KP9X hang-up sequence.

Dialing an Autodial Number Stored in the TIF-951

- 1 Tap the **PHONE** key to activate dialing mode.
- 2 Tap "down" on the TIF talk key to latch it in the on position.
- 3 Tap **CLR** followed by the autodial number (01, 02, etc.).
- 4 When finished dialing, click the **PHONE** key again to exit dialing mode.
- 5 Hang up using the KP9X hang-up sequence.