

C1:
D-Type 25p male

C2:
D-Type 25p male

pin	colour	signal name		signal name	pin	colour	
18	1 wht	OUT AES 1a	PFL L/R	IN AES 1a	1	1 wht	Connector: C3 Monitor Fr. C D1-1
6	1 brn	OUT AES 1b		IN AES 1b	9	1 brn	
19	1 scr	OUT AES 1scr		IN AES 1scr	2	1 scr	
4	2 wht	OUT AES 2a		IN AES 2a	11	2 wht	
17	2 grn	OUT AES 2b	CR L/R	IN AES 2b	3	2 grn	D-Type 15p male
5	2 scr	OUT AES 2scr		IN AES 2scr	10	2 scr	
15	3 wht	OUT AES 3a	CR C/SUB	IN AES 3a	15	3 wht	
3	3 yel	OUT AES 3b		IN AES 3b	7	3 yel	
16	3 scr	OUT AES 3scr	CR Ls/Rs	IN AES 3scr	14	3 scr	D-Type 15p male
1	4 wht	OUT AES 4a		IN AES 4a	5	4 wht	
14	4 gry	OUT AES 4b		IN AES 4b	13	4 gry	
2	4 scr	OUT AES 4scr		IN AES 4scr	6	4 scr	
24	5 wht	IN AES 1a	TB INT	IN AES 5a	1	6 wht	Connector: C4 Monitor Fr. C D2-1
12	5 pink	IN AES 1b		IN AES 5b	9	6 blu	
25	5 scr	IN AES 1scr		IN AES 5scr	2	6 scr	
10	—	IN AES 2a		OUT AES 2a	11	5 wht	
23	—	IN AES 2b	ST1 L/R	OUT AES 2b	3	5 pink	D-Type 15p male
11	—	IN AES 2scr		OUT AES 2scr	10	5 scr	
21	—	IN AES 3a		IN AES 1a	15	8 wht	
9	—	IN AES 3b		IN AES 1b	7	8 blk	
22	—	IN AES 3scr	ST2 L/R	IN AES 1scr	14	8 scr	D-Type 15p male
7	—	IN AES 4a		IN AES 2a	5	9 wht	
20	—	IN AES 4b		IN AES 2b	13	9 vio	
8	—	IN AES 4scr		IN AES 2scr	6	9 scr	
13	—	not connected					
18	6 wht	OUT AES 5a	CR Lc/Rc	n.c.			
6	6 blu	OUT AES 5b					
19	6 scr	OUT AES 5scr					
4	7 wht	OUT AES 6a					
17	7 red	OUT AES 6b	RES.	n.c.			
5	7 scr	OUT AES 6scr					
15	8 wht	OUT AES 7a					
3	8 blk	OUT AES 7b					
16	8 scr	OUT AES 7scr	ST1 L/R	n.c.			
1	9 wht	OUT AES 8a					
14	9 vio	OUT AES 8b					
2	9 scr	OUT AES 8scr					
24	0 wht	IN AES 5a	RES.	n.c.			
12	0 org	IN AES 5b					
25	0 scr	IN AES 5scr					
10	—	IN AES 6a					
23	—	IN AES 6b	ST1 L/R	n.c.			
11	—	IN AES 6scr					
21	—	IN AES 7a					
9	—	IN AES 7b					
22	—	IN AES 7scr	ST2 L/R	n.c.			
7	—	IN AES 8a					
20	—	IN AES 8b					
8	—	IN AES 8scr					
13	—	not connected					

