

Procedure to update the IPG-3901 SPI flash and SD card to Version 1.3.2

- Extract update package (3036-01P80-132_IPG-3901-iControl_7.10+_Upgrade_Package_v1.3.2.zip); you will get this extracted folder:

3036-01P80-132_IPG-3901-iControl_7.10+_Upgrade_Package_v1.3.2

- Remove SD card from IPG-3901 board and insert it into your PC SD card reader;

- Copy files to the SD card update partition:

- To update the SPI flash (U28), copy the <extracted folder>/u-boot-spi.bin file to SD card <update partition>.

- To update the SD card content, copy the <extracted folder>/rootfs.tar file to SD card <update partition>.

- Remove SD card from your PC SD card reader and put it back into IPG-3901 board;

- Power up IPG-3901 board and let it run;

- Wait for the yellow LED to turn red or green;