



X85-RCP/X75-RCP Release Notes

Version 3.9

Download Filename: x85x75-rel3.9.zip

Release Date: 3/9/2012

RELEASE SUMMARY

This release contains various updates for X50 product control

UPGRADING MODULE FIRMWARE

FTP Upload Procedure

After downloading the latest X75 file, please unzip the file in your local hard drive and make the following folder.

Eg: **C:\X75\FRAME**

Open up the DOS Command Prompt and go to the directory where the files were unzipped.

Eg: **CD C:\X75\FRAME** and press <ENTER> key.

Ping the IP address of the unit to validate the network connection.

Eg: **ping 192.168.100.250**

Note: If the connection is valid, four successful reply messages should be received.

Upload the files using FTP batch file called **X75FRAME.BAT**:

Syntax: **X75FRAME <IP address of the unit>**

Eg: **x75frame 192.168.100.250 <ENTER>**

Note: Wait 5~10 minutes until all the files are uploaded.

Reboot the unit.

Upload using CoPilot/Pilot/Navigator

Software requirement

CoPilot/Pilot version: 2.99 or greater

Navigator version: 2.1 or greater

X75: 1.4 or higher

Note: Only the X75 software release versions 1.5 or above will work with the above applications and multiple frames upload is possible.

If you need to go back to the old version, the FTP transfer method must be used.

Start the CoPilot/Pilot/Navigator application.

If the X75 has not been discovered and not registered in the application, then set the application in **BUILD** mode and follow the instructions below to start the discovery.

- Select **Options** button on the lower left corner and add the IP address of the frame(s) and press **OK** to exit the "Discovery Option" pane.
- Press the **Start** button to initiate the discovery process.
- Press the **Save** button to confirm.

Select **Tools > Software Upgrade** option and select the X75 frame(s) by pressing the **ADD** button.

Press the **Browse** button and select the downloaded latest version of X75 zipped file.

Press the **Submit Transfer** button.



X85-RCP/X75-RCP Release Notes

Version 3.9

Download Filename: x85x75-rel3.9.zip

Release Date: 3/9/2012

Release 3.9

Features

Proc, Black Level, etc. buttons are now mapped to appropriate parameter selections when remotely controlling an X50 unit

Parameter names on the front panel display are automatically shortened, if necessary, when controlling remote units



X85-RCP/X75-RCP Release Notes

Version 3.9

Download Filename: x85x75-rel3.9.zip

Release Date: 3/9/2012

Release 3.5

Notes

When saving favourites on the DPS-575 using the X75/X85 RCP, press shift before the User1/User2 button



X85-RCP/X75-RCP Release Notes

Version 3.9

Download Filename: x85x75-rel3.9.zip

Release Date: 3/9/2012

Release 1.8.127

Features

Added “[Please Wait...](#)” pop-up window on LCP/RCP display when a control parameter change is not immediate