

[Internal Use Only] <<The information in this document should not be used for other purpose than Sony and/or Sony authorized dealers (ASC/ASD).>>

Sony Corporation

No. DPMO13-017-TN

Technical News

Issued : November 12, 2013

Subject: Software Release (V1.03, V1.11, V1.01)

[Applicable Model]

| Model / Destination | Serial Number | Number of Unit |
|---------------------|---------------|----------------|
| PVM-1741 | 3000001 - | |
| PVM-1741 | 3100001 - | |
| PVM-1741 | 7000001 - | |
| PVM-1741(CN) | 5000001 - | |
| PVM-1741(CN) | 5100001 - | |

[Description]

There was a case that the tally lights up when turning on the power in rare cases. The following upgrade version is released.

Upgrade the software as necessary.

[Compatible Combinations for Installation]

The following 3 types of software are released for the corresponding functions.

1. Initial release model: V1.03
2. Flicker Free model: V1.11
3. Closed Caption model: V1.01

| From \ To | V1.03 | V1.11 | V1.01 | Applicable function |
|-----------|-------|-------|-------|---------------------------------|
| V1.01 | OK | NG | NG | Initial release Flicker Free |
| V1.02 | OK | NG | NG | |
| V1.10 | NG | OK | NG | |
| V1.00 | NG | NG | OK | Closed Caption |

[Applicable Serial No.]

Be sure to install the software that corresponds to the device serial number and software version.

| Applicable function | Serial No. | Version before change | | Version after change |
|---------------------------------|-------------------|-----------------------|----------|----------------------|
| Initial release Flicker Free | 3000001 - 3099999 | V1.01 - 1.02 V1.10 | -> -> | V1.03 V1.11 |
| | 5000001 - 5099999 | | | |
| | 7000001 - 7099999 | | | |
| Closed Caption | 3100001 - 3199999 | V1.00 | -> | V1.01 |
| | 5100001 - 5199999 | | | |

[Change Point]

<Error corrections>

Improvement of the tally's unintended lighting

[Preparation]

<Software file>

File name:

| | |
|-------------------------|----------------------|
| <Initial release model> | PVM1741_V1.03.zip |
| <Flicker Free model> | PVM1741_FF_V1.11.zip |
| <Closed Caption model> | PVM1741_CC_V1.01.zip |

* To obtain the above software, please contact your local Sony service office.

<Other>

- PC (OS: Windows Vista, Windows 7)
- Serial cable for writing the main unit software (1-831-247-11)
(For the PC without a serial port, a USB to serial port conversion cable is necessary.)

[Installation Procedure]

<Condition>

The software to be installed differs depending on the serial No. and the version.

Refer to the list in [Applicable Serial No.].

- * The version can be checked in the Service mode. For how to enter the Service mode, refer to the Service Manual.

<Procedure>

Refer to Technical News DPMO07-039.

In DPMO07-039, the model name is LMD-2450W, so read it as PVM-1741.

[Confirmation/Adjustment]

After installation, confirm that the version is correct and that it operates correctly.