

Technical Bulletin

81-9059-0415-0 A

Jaguar Video 220-260VAC Cooling Retrofit Kit

PRODUCT: Jaguar Video Routing Switcher

DATE: August 28, 1998

PROBLEM: Premature failures of the Jaguar Video PS130 power supplies have been traced to insufficient air flow through the power supplies of those routing switchers using 220-260VAC power sources.

SOLUTION: A retrofit kit (Part No. 81-9065-xxxx-0) has been developed to increase the flow of cooling air through the power supplies. This kit contains a door assembly, a power supply shipping bracket, and two power supply bay blank off plates. These parts are installed as follows:

1. Remove the existing power supply shipping bracket.
2. Install one blank off plate to the new power supply shipping bracket for each location where a power supply is not installed. If your routing switcher has four power supplies installed, none of these blank off plates will be used.
3. Install the new power supply shipping bracket.
4. Install the new door assembly.
5. Discard old parts.