

QUICK REFERENCE GUIDE

CAREL CONTROLLER: PCO 3 Small- Program 4.0v

MAIN MENU

- ❖ Main Screen – Displays current room temperature, setpoint and system status
- ❖ System Status Screens – Displays current room temperature, pressure, humidity, demands and outputs
- A. On/Off unit – Enable and disable system, change unit and system modes, and displays lead unit
- B. Set Points – Ability to change temperature, humidity and dehumidification set points.
- C. Factory menu – Factory set and factory authorized changes only
- D. Run Times – Displays run hours of all components.
- E. Min/Max reading – Displays min and max temperature, pressure and humidity in last 24 hours.
- F. Network status – Display status of devices on the network.
- G. Alarm history – Shows all past alarms with time and date
- H. Information – Displays Program version and revision date, Bios and Boot version, etc.
- I. Password – View/change level 1 password, enable auto screen lock, enable password to unlock
- J. Set Date/Time – Ability to adjust the time and date.

CHANGE SET POINTS

- Press ↑ or ↓ to change the setpoint to desired temperature

VIEW SYSTEM STATUS SCREENS

- Press the **PRG** to view status screens
- Press ↑ or ↓ to scroll through status screens

CHANGE MODE

- Press ←
- Press ↑ or ↓ twice. When cursor is flashing on "Unit Mode" press ↑ or ↓ to select desired mode.
- Press ← to return to the "Main Screen"

VIEW ALARM HISTORY

- Press **PRG** twice to view status screens
- Press the ↓ to highlight "Alarm History"
- Press the ←
- Press ↓ to view past alarms
- Press **ESC** twice to exit alarm history and return to the "Main Screen"

TO UNLOCK DISPLAY- ***LOCKED***

- Press and hold **ESC** and ↑ for 5 Seconds to unlock
- Enter Password if required: using ↑ or ↓ & ←.
- PSWD: 9999

TO VIEW CURRENT ALARMS

- Press 
- Press ↓ to view
- Press ← when prompted to clear current alarms

TO ACCESS MAIN MENU

- Press **PRG** twice
- Press ↑ or ↓ to view selections A. to J.
- Press ← when desired selection is highlighted
- Some selections may be password protected

*** AT ANY TIME, THE ESC KEY TO GET BACK TO THE MAIN SCREENS ***

